



# Vending Machine Compatibility

For support questions please email:

[LYNKSupport@globalconnect.biz](mailto:LYNKSupport@globalconnect.biz)

For EPROM/FW consultation please email:

[parts@veii.com](mailto:parts@veii.com)

---

|                                        |   |
|----------------------------------------|---|
| AMS .....                              | 2 |
| AUTOMATIC PRODUCTS (AP).....           | 2 |
| CRANE NATIONAL.....                    | 4 |
| DIXIE NARCO .....                      | 5 |
| ROYAL .....                            | 6 |
| VENDO .....                            | 7 |
| USI.....                               | 7 |
| OTHER KNOWN COMPATIBILITY ISSUES ..... | 9 |
| VE PARTS LIST AND PART #S: .....       | 9 |

## AMS

Machines that are compatible with LYNK devices:

| Machine / Make / Model                      | EPROM FW Version | DEX Adapter Kit? | Notes                                                     |
|---------------------------------------------|------------------|------------------|-----------------------------------------------------------|
| <b>AMS SENSIT 1</b>                         | 10227            | YES              |                                                           |
| <b>Snack SENSIT 2</b>                       | 3248AL           | YES              |                                                           |
| <b>Combo SENSIT 2</b>                       | 3249AL           | NO               |                                                           |
| <b>Refrigerated Health Control SENSIT 2</b> | 3250AL           | NO               |                                                           |
| <b>Refrigerated Health Control SENSIT 3</b> | 3427 V1.41       | NO*              | * Depending on location of DEX port (in cabin or in door) |

## Automatic Products (AP)

Machines that are compatible with LYNK devices:

| Machine / Make / Model              | Special Requirements  | EPROM FW Version              | DEX Adapter Kit? | Notes                                             |
|-------------------------------------|-----------------------|-------------------------------|------------------|---------------------------------------------------|
| <b>110 up to 113 Series</b>         | Surface Mount on door | V.E. UCB with Rev 3.2.1       | NO               | Needs a InOne or VE UCB.                          |
| <b>120 Series Glassfront</b>        | Surface Mount on door | rev 5.24 or later             | NO               |                                                   |
| <b>130 Series Glassfront</b>        | Surface Mount on door | rev 0024 or later             | YES              | DEX Adapter Kit needed if the board is a ST or SL |
| <b>Studio Series</b>                | Surface Mount on door | rev 069 for SL rev 024 for ST | YES              | AP Studio I – No Support, machine outdated.       |
| <b>223 Hot Beverage</b>             | Surface Mount on door | 6.13                          |                  |                                                   |
| <b>320 Studio Series Glassfront</b> | Surface Mount on door | 5.28                          |                  |                                                   |

|                                                    |                          |                                    |     |                                                                      |
|----------------------------------------------------|--------------------------|------------------------------------|-----|----------------------------------------------------------------------|
| <b>Premier Series Glassfront<br/>931, 932, 933</b> | Surface Mount on<br>door | rev 0069 for SL rev<br>0024 for ST | YES |                                                                      |
| <b>6500 Series Food Ultra<br/>Flex</b>             | Surface Mount on<br>door | Requires V.E.Smart<br>Board        |     | If upgraded with VE<br>Smart Boards, DEX Zero<br>Cable not required. |
| <b>962 &amp; 965 Series Food</b>                   | Surface Mount on<br>door | 432.08                             |     |                                                                      |
| <b>Cafforia Series Coffee<br/>942, 943, 944</b>    | Surface Mount on<br>door | N/A                                |     |                                                                      |
| <b>980, 981 Merchant</b>                           | Surface Mount on<br>door | 181.02.09                          |     |                                                                      |
| <b>933</b>                                         | Surface Mount on<br>door |                                    |     |                                                                      |

- If the AP machine with a ST board needs a factory reset, please click on the link below:  
[https://drive.google.com/file/d/1KkKpqFcSwC9d-sIQXzeKPgdRDYsyz1Sl/view?usp=drive link](https://drive.google.com/file/d/1KkKpqFcSwC9d-sIQXzeKPgdRDYsyz1Sl/view?usp=drive_link)

## Crane National

Machines that are compatible with LYNK devices:

| Machine / Make / Model                                                                             | EPROM FW Version                 | DEX Adapter Kit | Notes |
|----------------------------------------------------------------------------------------------------|----------------------------------|-----------------|-------|
| <b>Snack Center 157,158,167,168, 455, 464, 465,764, 765, 484, 485, 497, 780, 784, 785 &amp;797</b> | rev 158.29                       | NO              |       |
| <b>Snack Center 159, 160, 172, 173</b>                                                             | 160.11                           | NO              |       |
| <b>Frozen Food 455</b>                                                                             | rev 160.04 or later              | NO              |       |
| <b>Shopper 431</b>                                                                                 | 431.2                            | NO              |       |
| <b>Shopper 432, 962</b>                                                                            | 432.1                            | NO              |       |
| <b>Hot drink 633, 635, 637</b>                                                                     | 633.2                            | NO              |       |
| <b>Hot drink 653, 655, 657</b>                                                                     | 653.06.1                         | NO              |       |
| <b>Hot drink 673, 675, 677, 944, 945, 946, 947</b>                                                 | 673.05.04                        | NO              |       |
| <b>Seattle's Best 677</b>                                                                          | 677.05.5                         | NO              |       |
| <b>Hot drink 942, 946, 947</b>                                                                     | 673.05.04                        | NO              |       |
| <b>Hot drink 674, 676</b>                                                                          | 674.1                            | NO              |       |
| <b>180 /181 Series Glassfront</b>                                                                  | rev. 181.02.15 or newer          | NO              |       |
| <b>186 /187 Media</b>                                                                              | min -10.6.16<br>Latest – 10.12.9 | NO              |       |
| <b>471 / 472 Merchant</b>                                                                          | 10.11.5                          | NO              |       |
| <b>VOCE Coffee</b>                                                                                 | Min – 2.2.0                      |                 |       |

## Dixie Narco

Machines that are compatible with LYNK devices:

| Machine / Make / Model                             | EPROM FW Version                                                               | DEX Adapter Kit? | Notes                          |
|----------------------------------------------------|--------------------------------------------------------------------------------|------------------|--------------------------------|
| <b>276, 501,522 &amp; 576 (Pepsi: See NOTE 10)</b> | SD series controller 381.11<br>or later P series controller<br>240.81 or later | NO               |                                |
|                                                    |                                                                                |                  |                                |
|                                                    | Coke 390-51B (allows<br>combo vends)                                           |                  |                                |
| <b>DN 501 Pepsi HVV (See NOTE 10)</b>              | 240.81                                                                         | NO               |                                |
| <b>BevMax DN5591</b>                               | 30.61                                                                          | NO               |                                |
| <b>BevMax DN5800-3 &amp; 3800-3</b>                | 80.71                                                                          | NO               |                                |
| <b>BevMax DN5800-4 &amp; 3800-4</b>                | With red control board<br>740.51                                               | NO               |                                |
|                                                    |                                                                                |                  |                                |
|                                                    | With blue control board<br>701.91,701.11, 702.21                               |                  |                                |
|                                                    |                                                                                |                  |                                |
| <b>BevMax DN5800-6 &amp; 3800-6</b>                | 10.9.9 or 10.9.14                                                              | NO               |                                |
| <b>3800-4 REFRESH</b>                              | 269r02                                                                         |                  |                                |
| <b>DN 3000 &amp; 5000</b>                          | 991.51                                                                         | NO               |                                |
| <b>DN720P HVV</b>                                  | 870.61                                                                         |                  | USE HVV KIT<br>#V6XUK0101305** |
| <b>DN5591 and DN2145</b>                           | 30.81                                                                          |                  |                                |
| <b>DX-501-E – Coke (KO)</b>                        | 391.41 or newer                                                                | NO               |                                |
| <b>DX-501-E - Pepsi Machine</b>                    | 381.41 or newer                                                                | NO               |                                |

## Royal

Machines that are compatible with LYNK devices:

| Machine / Make / Model                                    | Special Requirements  | EPROM FW Version     | DEX Adapter Kit? | Notes |
|-----------------------------------------------------------|-----------------------|----------------------|------------------|-------|
| <b>Merlin Series RVMxxx</b>                               | Surface Mount on Door | 67100-12             | YES              |       |
| <b>G-III Series RVC 550-660-804</b>                       | Surface Mount on Door | 67325-2              | NO               |       |
| <b>G-III Series RVC 550-660-804 With Coke" Wave" door</b> |                       | 67325-2              | NO               |       |
| <b>HVV</b>                                                |                       | 67231-13             | NO               |       |
| <b>RVV 500 Glass front (see NOTES 7)</b>                  |                       | 67241-12 or 67246-12 | NO               |       |
| <b>RHVV 500 (PEPSI) (see NOTES 7)</b>                     | Surface Mount         | 67241-12 or 67246-13 | NO               |       |
| <b>RVRB Red Bull</b>                                      | on Door               | 67100-12             |                  |       |

## Vendo

Machines that are compatible with LYNK devices:

| Machine / Make / Model           | EPROM FW Version                             | DEX Adapter Kit? | Notes                        |
|----------------------------------|----------------------------------------------|------------------|------------------------------|
| <b>511 (480)</b>                 | 1.068 or later                               | YES              | AP fix or 1310 for STS issue |
| <b>540 Trade</b>                 | V20.20 or later                              | YES              |                              |
| <b>V-MAX 621-721-821</b>         | 123-3014                                     | YES              |                              |
| <b>719511008 (Branded Candy)</b> | rev. 2.09                                    |                  |                              |
| <b>720</b>                       | 2.042 supports                               | YES              |                              |
| <b>721 (Standard)</b>            | 2.042 supports                               | YES              |                              |
| <b>721 HVV Pepsi</b>             | Rev. 9.1                                     | YES              |                              |
| <b>Vue 30 – 40</b>               | 1144303-25                                   | YES              |                              |
| <b>V-21 Coke</b>                 | 1123052-24                                   | YES              |                              |
| <b>V-21 Pepsi</b>                | 1123053-24                                   | YES              |                              |
| <b>Vendo refresh</b>             | 12.4 rev 37 might not work with LYNK devices | YES              |                              |

## USI

Machines that are compatible with LYNK devices:

| Machine / Make / Model                                | EPROM FW Version            | DEX Adapter Kit? | Notes |
|-------------------------------------------------------|-----------------------------|------------------|-------|
| <b>SM 5700</b>                                        | 67185-8                     |                  |       |
| <b>Alpine VT-3000 &amp; VT-5000</b>                   | GVC1 2410 GVC2 5332         | NO               |       |
| <b>Alpine ST-3000 &amp; ST-5000</b>                   | GVC1 2410 GVC2 5332         | NO               |       |
| <b>3814</b>                                           | N/A                         | NO               |       |
| <b>3053</b>                                           | SM6 board 67185-8           | NO               |       |
| <b>3129</b>                                           | 67093-4                     | NO               |       |
| <b>3160 – 3169 – 3185</b>                             | SM6 board 67185-8 & 67209-6 | NO               |       |
| <b>3535</b>                                           | GVC2controller 2.8.8523     | NO               |       |
| <b>Mercato M-3000, M-3000, M-4000, M-5000, M-7000</b> | GVC1 2410 GVC2 5332         | NO               |       |
| <b>Summit 500 &amp; 700</b>                           | GVC1 2410 GVC2 5332         | NO               |       |



|                            |  |            |  |
|----------------------------|--|------------|--|
| Evoked                     |  | NO         |  |
| Alpine – 3561 Food Machine |  | GVC2 12189 |  |

## Other Known Compatibility Issues

| Machine / Make / Model                                   | Issue                                                                                                  | Resolution   | Notes                                                                                                                     |
|----------------------------------------------------------|--------------------------------------------------------------------------------------------------------|--------------|---------------------------------------------------------------------------------------------------------------------------|
| <b>TRC 6512, MEI Mars</b>                                | Coin mech causes LYNK to Initialize on National 167 with each coin inserted                            | Castles NPC4 | Contact VE for the Castles NPC cable at no cost. This will resolve issue.                                                 |
| <b>Coinco 9302 GX Coin Mech</b>                          | LYNK reboots when this coin mech is installed                                                          | Castles NPC4 | Contact VE for the Castles NPC cable at no cost. This will resolve issue.                                                 |
| <b>CPI Gryphon Coin Changer and Talos bill validator</b> | Having both Gryphon coin changer and Talos bill validator causes LYNK to stay on Init MDB after reboot | Castles NPC4 | Remove/replace either Gryphon or Talos then LYNK works. If cable needed, contact VE for the Castles NPC cable at no cost. |
| <b>Coinco MAG bill validator</b>                         | Doesn't line up with overlay                                                                           | N/A          | Vantage Coinco align well.<br>Use Full size LYNK with MAG Coinco                                                          |

## VE Parts List and Part #s:

| LYNK ACCESSORIES |                                                         | Part#     |
|------------------|---------------------------------------------------------|-----------|
| CABLES           | Full size DEX adapter kit/cable for Vendo and older VMC | VE6793    |
|                  | Overlay DEX adapter kit/cable for Vendo and older VMC   | VE6793U1B |
|                  | Power noise MDB cable for full size (67X, 43X)          | VE6799    |
|                  | 15 ft DEX extension harness                             | VE1020268 |
|                  | 14 ft MDB extension harness                             | VE1020161 |
|                  | 16 ft antenna extension cable                           | VED6220   |
|                  | High gain antenna with 6' extension                     | VED5191   |
|                  | DEX Y Connector for Vendmax                             | VE1016702 |
| BRACKETS         | .75 inch riser for LYNK full size                       | VE6790    |
|                  | Full size mounting bracket for Vendo                    | VE1020291 |
|                  | Mounting bracket for LYNK for Saturn reader             | VE1021076 |
|                  | Mounting for LYNK for Vivotech reader                   | VE1021075 |